



Current 1550 v4.7 Menu Map with Default Values

Date: May 31, 2013

The current firmware version for the Audio Authority Series 1500 Intercom System is version 4.7. To be able to access all system program parameters a Model 1550 Field Setup Tool is required. The following table is provided for reference of menu structure and factory default values where applicable.

Root Menu	First Menu Subset	Second Menu Subset	Financial Default Value	Pharmacy Default Value
1: System Parameters	1: Blower Motor Delay		3.0	3.0
	2: Power Save Delay**		90	90
	3: Supervisor Teller*		None	None
	4: Lane Mirror Disable**		Off	Off
	5: Traffic Sensor Tone		Use Lane Ringtone	Use Lane Ringtone
	6: Background Threshold		4	4
	7: Allow Video Scroll		On	Off
	8: Master Teller		None	1
2: Lane Parameters	1: Single Lane	1: Inbound Volume Level	8	8
	2: Auto Select Lane	2: Outbound Volume Level	4	4
	3: Group of Lanes	3: Open Loop Gain	12	12
	4: All Lanes	4: Handset Mic Level	8	8
	5: Cancel	5: Handset Speaker Level	8	8
		6: Ringtone Override	None	None
		7: Half Duplex Only	Off	Off
		8: Program Audio Abate	Off	Off
		9: Relay Operation	Selection Activates	Selection Activates
		10: Swap Camera Up/Down	Off	Off
		11: Suppress Video	Off	Off
3: Teller Parameters	1: This Teller	1: Key Assignment		
	2: Single Teller	2: Allow Hands Free	On	Off
	3: Group of Tellers			
	4: All Tellers			
	5: Cancel			

This document is for the exclusive use of Audio Authority and may contain confidential and/or proprietary information. The information contained herein cannot be copied, redistributed, or retransmitted in any way, in whole or in part, without written permission from Audio Authority



Root Menu	First Menu Subset	Second Menu Subset	Financial Default Value	Pharmacy Default Value
4: Set Defaults	1: Cancel			
	2: Financial Defaults			
	3: Pharmacy Defaults			
5: Memory Card	1: Cancel			
	2: Write To Memory Card			
	3: Read From Memory Card			
	4: Firmware Upgrade			
6: Exit	1: Cancel			
	2: Exit and Save			
	3: Exit Without Saving			

***Not Available with 1 on 1 configurations**

****Not available with 1509SD mini hub configurations**

The menu structure and default values presented here are subject to change in future hardware and or firmware version releases.

Document prepared by Duane Crowder

This document is for the exclusive use of Audio Authority and may contain confidential and/or proprietary information. The information contained herein cannot be copied, redistributed, or retransmitted in any way, in whole or in part, without written permission from Audio Authority

Audio Authority®
 2048 Mercer Road, Lexington, Kentucky 40511-1071 USA
 Toll-free US & Canada 800-322-8346 | Phone: 859-233-4599 | Hours: M-F 8:30am to 5:00pm EST
 Web: www.audioauthority.com