

Left/Right and Mono Speaker Hookup

Model 932 Speaker Modules can be configured to function as left, right or mono modules. The slide switch on the left side of the module is marked LEFT and RIGHT. Position the slide switch to LEFT for left channel function and toward RIGHT for right channel or MONO function. (If used for mono operation there will not be a corresponding "L" module.)

Model 932s are unique in that they share the same GROUP Address with the amplifier group with which they operate. For example, if the front amp GROUP number is "4," then the front speaker GROUP number would also be "4." Additionally, LEFT and RIGHT modules have the same MODULE ID; here is an example: For speakers 1-8, both LEFT & RIGHT 932 modules have the address: 4/00 (GROUP=4 / MODULE ID=00). For speakers 9-16 both LEFT & RIGHT 932 modules have the address: 4/01 (GROUP=4 / MODULE ID=01) etc...

